



XP Preamp specification and comparison sheet:

Specifications	XP-30	XP-20	XP-10
Overall Gain	-90 dB to +10 dB	-73 dB to +10 dB	-73 dB to +10 dB
Volume steps	99	83	83
Remote	Yes	Yes	Yes
Inputs	6	5	5
Outputs	4	2	2
Frequency Response	-3dB @ 2 Hz and 60 kHz	-3dB @ 2 Hz and 60 kHz	-3dB @ 2 Hz and 60 kHz
Input Impedance	42k balanced	96k bal, 48k single-ended	96k bal, 48k single-ended
Output Impedance	120 Ohm bal, 120 Ohm SE	1000 Ohm bal, 150 Ohm SE	1000 Ohm bal, 150 Ohm SE
CMRR	-60 dB, 1 kHz	-60 dB, 1 kHz	-60 dB, 1 kHz
Cross-talk	-100 dB, 1kHz Ref 1V	-90 dB, 1kHz Ref 1V	-90 dB, 1kHz Ref 1V
Signal to Noise Ratio	< -110 dB, Ref 5V	< -110 dB, Ref 5V	< -110 dB, Ref 5V
Power Consumption	45 watts	25 watts	10 watts
Number of chassis	3	2	1
Dimensions, Each Chassis	17"W x 12"D x 4"H	17"W x 12"D x 4"H	17"W x 12"D x 4"H
Shipping Weight (LBS)	75	50	32